

### 选件



### 型号

| 型号            | 额定功率<br>W | 额定转矩<br>Ncm | 额定电流<br>A | 峰值电流<br>A | 标称电压<br>V | 额定转速<br>rpm | 转矩常数<br>Ncm/A | 转子的转动惯量<br>gcm <sup>2</sup> | 机身长度 "A"<br>mm | 重量<br>kg |
|---------------|-----------|-------------|-----------|-----------|-----------|-------------|---------------|-----------------------------|----------------|----------|
| DB41S024030-A | 22        | 7           | 1.3       | 4.4       | 24        | 3000        | 5.42          | 48                          | 40.3           | 0.3      |
| DB41M024030-A | 50        | 16          | 3         | 9.2       | 24        | 3000        | 5.41          | 101                         | 60.3           | 0.45     |
| DB41L024030-A | 82        | 26          | 4.8       | 14.8      | 24        | 3000        | 5.4           | 154                         | 80.3           | 0.65     |
| DB41C024030-A | 113       | 36          | 6.7       | 22.2      | 24        | 3000        | 5.4           | 207                         | 100.3          | 0.8      |

### 配件

- ZD-D28 减震器
- ZD-D40 减震器
- ZD-DF40 减震器

### 尺寸图 (单位MM)

